

## 100V N-Channel Enhancement Mode MOSFET

### Description

The AP4N10MI uses advanced trench technology to provide excellent  $R_{DS(ON)}$ , low gate charge and operation with gate voltages as low as 4.5V. This device is suitable for use as a Battery protection or in other Switching application.

### General Features

$V_{DS} = 100V$   $I_D = 3.8A$



$R_{DS(ON)} < 250m\Omega$  @  $V_{GS}=10V$  (Type: **200mΩ**)

### Application

LED


Load switch

Uninterruptible power supply



Top View

Bottom View



### Package Marking and Ordering Information

Product ID	Pack	Marking	Qty(PCS)
AP4N10MI	SOT23-3L	MA5	3000

### Absolute Maximum Ratings ( $T_C=25^\circ\text{C}$ unless otherwise noted)

Symbol	Parameter	Rating	Units
$V_{DS}$	Drain-Source Voltage	100	V
$V_{GS}$	Gate-Source Voltage	$\pm 20$	V
$I_D@T_A=25^\circ\text{C}$	Continuous Drain Current, $V_{GS} @ 10V^1$	3.8	A
$I_D@T_A=100^\circ\text{C}$	Continuous Drain Current, $V_{GS} @ 10V^1$	2	A
$I_{DM}$	Pulsed Drain Current <sup>2</sup>	8	A
$P_D@T_A=25^\circ\text{C}$	Total Power Dissipation <sup>3</sup>	3.75	W
$T_{STG}$	Storage Temperature Range	-55 to 150	$^\circ\text{C}$
$T_J$	Operating Junction Temperature Range	-55 to 150	$^\circ\text{C}$
$R_{\theta JA}$	Thermal Resistance Junction-ambient <sup>1</sup>	125	$^\circ\text{C}/\text{W}$
$R_{\theta JC}$	Thermal Resistance Junction-Case <sup>1</sup>	30	$^\circ\text{C}/\text{W}$



## 100V N-Channel Enhancement Mode MOSFET


### Electrical Characteristics ( $T_J=25^{\circ}\text{C}$ , unless otherwise noted)

Symbol	Parameter	Test Condition	Min.	Typ.	Max.	Unit
V(BR)DSS	Drain-Source Breakdown Voltage	VGS = 0 V, ID = 250 $\mu$ A	100	111	-	V
IGSS	Gate Leakage Current	VGS = $\pm$ 20V, VDS = 0V	-	-	$\pm$ 100	nA
IDSS	Drain Cut-off Current	VDS = 100V, VGS = 0V	-	-	1	$\mu$ A
VGS(th)	Gate Threshold Voltage	VGS = VDS, ID = 250 $\mu$ A	1.2	1.6	2.5	V
RDS(on)	Drain-Source on-state Resistance <sup>3</sup>	VGS = 10V, ID = 2A	-	200	250	m $\Omega$
		VGS = 4.5V, ID = 1.5A	-	220	280	
Ciss	Input Capacitance	VGS = 0V, VDS = 50V, f = 1MHz	-	440	-	pF
Coss	Output Capacitance		-	14	-	pF
Crss	Reverse Transfer Capacitance		-	10	-	pF
Qg	Total gate charge	VGS = 10V, VDS = 50V, ID = 2A	-	5.3	-	nC
Qgs	Gate-source charge		-	1.4	-	nC
Qgd	Gate-drain charge		-	1.8	-	nC
td(on)	Turn-on Time	VGS = 10V, VDD = 50V, RG = 1 $\Omega$ , ID = 2A	-	14	-	ns
tr	Rise time		-	54	-	ns
td(off)	Turn-off Time		-	18	-	ns
tf	Fall time		-	11	-	ns
VSD	Body Diode Voltage <sup>3</sup>	IS = 1A, VGS = 0V	-	-	1.2	V
IS	Continuous Source Current		-	-	2	A


#### Note :

- 1、 The data tested by surface mounted on a 1 inch<sup>2</sup> FR-4 board with 2OZ copper.
- 2、 The data tested by pulsed , pulse width  $\cong$  300us , duty cycle  $\cong$  2%
- 3、 The power dissipation is limited by 150 $^{\circ}$ C junction temperature
- 4、 The data is theoretically the same as ID and IDM , in real applications , should be limited by total power dissipation.


**Typical Characteristics**




**Figure 1. Output Characteristics**




**Figure 2. Transfer Characteristics**




**Figure 3. Forward Characteristics of Reverse**



**Figure 4. RDS(ON) vs. VGS**




**Figure 5. RDS(ON) vs. ID**




**Figure 6. Normalized R DS(on) vs. Temperature**


**100V N-Channel Enhancement Mode MOSFET**




**Figure 7. Capacitance Characteristics**




**Figure 8. Gate Charge Characteristics**



**Fig.9 Normalized Maximum Transient Thermal Impedance**




**Fig.10 Switching Time Waveform**



**Fig.11 Unclamped Inductive Switching Waveform**

### Package Mechanical Data-SOT23-3-XC-Single



Symbol	Dimensions In Millimeters	
	Min.	Max.
A	1.050	1.250
A1	0.000	0.100
A2	1.050	1.150
b	0.25	0.45
c	0.100	0.200
D	2.820	3.020
E	1.5	1.7
E1	2.650	2.950
e	0.950(BSC)	
e1	1.800	2.000
L	0.300	0.500
$\theta$	0°	8°

**100V N-Channel Enhancement Mode MOSFET****Attention**

1, Any and all APM Microelectronics products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your APM Microelectronics representative nearest you before using any APM Microelectronics products described or contained herein in such applications.

2, APM Microelectronics assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges, or other parameters) listed in products specifications of any and all APM Microelectronics products described or contained herein.

3, Specifications of any and all APM Microelectronics products described or contained here instipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.

4, APM Microelectronics Semiconductor CO., LTD. strives to supply high quality high reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.

5, In the event that any or all APM Microelectronics products (including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.

6, No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of APM Microelectronics Semiconductor CO., LTD.

7, Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. APM Microelectronics believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

8, Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the APM Microelectronics product that you intend to use.

**100V N-Channel Enhancement Mode MOSFET**

<b>Edition</b>	<b>Date</b>	<b>Change</b>
Rve3.8	2020/5/1	Initial release
Rve3.9	2022/3/1	Transfer 12 inches

**Copyright Attribution“APM-Microelectronice”**